1.1.2.2 High Sensitivity Thermal Sensors

8μW to 3W

Features

- Very low noise and drift to measure very low powers and energies
- Broadband and P absorbers for CW and short pulses
- Up to 3W
- Version for Terahertz








| Model | 3A-P-THz | 3A-FS | 3A-P-FS-12 |
|---|---|--------------------------|--|
| Use | Calibrated for Terahertz radiation | With removable window | For divergent beams, window blocks infrared |
| Absorber Type | P type | Broadband + F.S. window | P type + F.S. window |
| Spectral Range µm | 0.1THz - 30THz (c) | 0.19 - 20 ^(b) | 0.22 - 2.1 |
| Aperture mm | Ø12mm | Ø9.5mm | Ø12mm |
| Maximum Beam Divergence | NA | NA | ±40 degrees |
| Power Mode | | | |
| Power Range (f) | 15μW - 3W | 8μW - 3W | 15μW - 3W |
| Power Scales | 3W to 300µW | 3W to 300μW | 3W to 300µW |
| Power Noise Level | 4µW ^(d) | 2µW | 6μW |
| Thermal Drift (30min) (a) | 5 - 30μW | 2 - 10μW | 20 - 40µW |
| Maximum Average Power Density kW/cm ² | 0.05 | 1 | 0.05 |
| Response Time with Meter (0-95%) typ. s | 2.5 | 1.8 | 2.5 |
| Power Accuracy +/-% | 8 ^(c) | 3 | 3 |
| Linearity with Power +/-% | 1 | 1 | 1 |
| Energy Mode | | | |
| Energy Range | 20uJ - 2J | 15µJ - 2J | 20µJ - 2J |
| Energy Scales | 2J to 200µJ | 2J to 200µJ | 2J to 200µJ |
| Minimum Energy | 20µJ | 15µJ | 20µJ |
| Maximum Energy Density J/cm ^{2 (e)} | 2000 | .5 μ | 2003 |
| <100ns | 1 | 0.3 | 1 |
| 0.5ms | 1 | 1 | 1 |
| 2ms | 1 | 2 | 1 |
| 10ms | 1 | 4 | 1 |
| Cooling | convection | convection | convection |
| Weight kg | 0.2 | 0.2 | 0.15 |
| Fiber Adapters Available (see page 83) | ST, FC, SMA, SC | ST, FC, SMA, SC | NA |
| Version | 31,1 C, 3111 1, 3C | 31,1 C, 3111 1, 3C | |
| Part number | 7Z02742 | 7Z02628 | 7Z02687 |
| Note: (a) | Depending on room airflow and tem | | , |
| Note: (b) | Remove window for measurement beyond 2.2µm | | |
| Note: (c) | 2 sigma standard lab traceable calibration for 0.6THz – 10THz. For 0.3 - 0.5THz add 4% to error. | | |
| • | Outside this region the sensor will measure but is not calibrated. | | |
| Note: (d) | Back reflections from meter can sometimes cause interference effects with source. Unit should be tilted ~10° in this case | | |
| Note: (e) For P type and shorter wavelengths derate | Wavelength Derate to value | | |
| maximum energy density as follows: | 1064nm Not derated | | |
| | 532nm Not derated | | |
| | 355nm 40% of stated value | | |
| | 266nm 5% of stated value 193nm 10% of stated value | | |
| Note: (f) | Lowest measurable powers are achieved by thermally quiet room conditions, using removable snout, averaging and offset | | |
| | subtraction | | |

3A-P-THz



Ophir®

